

PRODUCT-DETAILS

PSE30-600-70

PSE30-600-70 Softstarter



General Information

Global Commercial Alias	PSE30-600-70
Extended Product Type	PSE30-600-70
Product ID	1SFA897103R7000
ABB Type Designation	PSE30-600-70
EAN	7320500400616
Catalog Description	PSE30-600-70 Softstarter

Long Description

The softstarter PSE30-600-70 has a rated maximum operational current of 30 A with an operating voltage span from 208...600 V AC. The rated control voltage is between 100...250 V AC at 50/60 Hz. PSE features a two-phase control with a soft start and stop through a voltage or a torque ramp. It has a built-in bypass for easy installation and energy saving. A RUN, TOR, and Event signal is available from a relay output in NO (normally open state). The PSE has functions such as current limit, kickstart, analog output, EOL, underload, and locked rotor protection. To interact with PSE, it has an illuminated display that uses symbols to become language neutral. As an option, you can add an identical external keypad with a rating of IP66. There are three ways to communicate with PSE. It can be done by hardwire inputs Start/Stop or by Reset of fault. Another popular option is the built-in Fieldbus communication Modbus RTU, but we can also use an external adaptor and a Fieldbus plug.

The new generation PSE is a true general purpose softstarter. It's a perfect balance between high starting capacity and cost efficiency. It is now featuring built-in Fieldbus communication. They are suitable for small to medium-sized three-phase motors with nominal currents from 18...370 A. Typical applications are, for example, pumps, fans, compressors, and conveyors.

Ordering

Minimum Order Quantity	1 piece
Customs Tariff Number	85044090

Popular Downloads

Data Sheet, Technical Information	1SFC132012C0201
Instructions and Manuals	1SFC132057M0201

Dimensions

Product Net Width	90 mm
Product Net Height	245 mm
Product Net Depth / Length	184 mm
Product Net Weight	2.5 kg

Technical

Rated Operational Voltage	208 ... 600 V AC
Rated Control Supply Voltage (U_s)	100 ... 250 V AC
Rated Control Circuit Voltage (U_c)	DC Operation 24 V
Rated Frequency (f)	50/60 Hz Main Circuit 50 / 60 Hz
Rated Operational Power - In-Line Connection (P_e)	(230 V) 7.5 kW (400 V) 15 kW (500 V) 18.5 kW
Rated Operational Current - In-Line Connection (I_e)	30 A
Service Factor Percentage	100 %
Overload Protection	Build-in electronic overload protection
Integrated Electronic Overload	Yes
Adjustable Rated Motor Current I_e	30 ... 100 %
Starting Capacity at Maximum Rated Current I_e	4xle for 10s
Ramp Time	0 ... 30 second [unit of time] 1 ... 30 second [unit of time]
Initial Voltage During Start	30 ... 70 %
Step Down Voltage Special Ramp	No %
Current Limit Function	1.5 ... 7xle
Switch for Inside Delta Connection	No
Run Signal Relay	Yes
By-pass Signal Relay	Yes
Fault Signal Relay	Yes

Overload Signal Relay	Yes
Analog Outputs	4...20 mA
Signal indication completed start ramp (LED)	Green
Signal indication ready to start/standby ON (LED)	Green
Signal indication running R (LED)	Green
Signal indication ramping up/down (LED)	Green
Signal indication protection (LED)	Yellow
Signal indication fault (LED)	Red
Number of Starts Per Hour at 3.5*Ie for 7 sec. 50% ON Time 50% OFF Time	10
Communication	FiledBusPlug(Optional)
Degree of Protection	IP00
Terminal Type	Screw Terminals
Connecting Capacity Main Circuit	Hole Diameter 8.5 mm Rigid 1/2 x 2.5 ... 70 mm² Width and Thickness 17.5x5 mm
Connecting Capacity Control Circuit	Rigid 1 x 2.5 mm² Rigid 2 x 1.5 mm²
Connecting Capacity Supply Circuit	Rigid 1 x 2.5 mm²
Tightening Torque	Control Circuit 0.5 N·m Main Circuit 9 N·m Supply Circuit 0.5 N·m
Product Main Type	PSE30

Technical UL/CSA

Maximum Operating Voltage UL/CSA	Main Circuit 600 V
Tightening Torque UL/CSA	Control Circuit 4.4 in·lb Main Circuit 79.7 Supply Circuit 4.4 in·lb

Environmental

Ambient Air Temperature	Operation -25 ... +60 °C Storage -40 ... +70 °C
RoHS Status	Following EU Directive 2002/95/EC August 18, 2005 and amendment

Certificates and Declarations (Document Number)

CQC Certificate	CQC2011010304468093
Declaration of Conformity - CCC	2020980304001546
Declaration of Conformity	2CMT2015-005447

- CE

Environmental Information	1SFC132042D0201
Instructions and Manuals	1SFC132057M0201
RoHS Information	1SFC132043D0201

Container Information

Package Level 1 Width	178 mm
Package Level 1 Depth / Length	257 mm
Package Level 1 Height	288 mm
Package Level 1 Gross Weight	3.2 kg
Package Level 1 EAN	7320500400616
Package Level 1 Units	box 1 piece

Classifications

Object Classification Code	Q
ETIM 4	EC002572 - Electronic motor control and protection device
ETIM 5	EC002572 - Electronic motor control and protection device
ETIM 6	EC002572 - Motor management device
eClass	V11.0 : 27370907
UNSPSC	39121521

Categories

Drives → Softstarters → Softstarters → PSE Softstarters → PSE30

Low Voltage Products and Systems → Control Products → Softstarters → Softstarters → PSE Softstarters → PSE30

