

LED VALUE T26 LAMP









Product licensee of trademark
OSRAM in general lighting



LED VALUE T26 LAMP



Item name	Product number (EAN)	W ¹		lm ¹	K	R _a	 ²		 l [mm]	 d [mm]	 ³ t [h]
T26 warm white	4058075509566	2.3	E14	200	2700	80	NO	160	63	25	15000
T26 day light	4058075509580	2.3	E14	200	6500	80	NO	160	63	25	15000

Benefits

- Extremely small dimensions
- Good all-around light emission
- Ideal for decorative and free-burning applications
- Long lifetime of up to 15,000 h

Key Features

- LED alternative to conventional high voltage lamps
- Good quality of light; color rendering index $R_a \geq 80$; constant chromaticity
- Instant brightness
- UV and IR radiation free
- Mercury free

Application Notice:

- Outdoor applications only in suitable luminaire
- Switch off the light during installation
- Input voltage: 220-240V
- Frequency: 50-60HZ
- Not for use with dimmers
- Not for use with closed or tight fixtures
- Storage temperature & humidity conditions (-20°C up to +80°C, at max. 95% relative humidity)
- Operating temperature & humidity conditions (-20°C up to +40°C, at max. 95% relative humidity)

Lamp conformity

- IEC 62560 Self-ballasted LED-lamps for general lighting services by voltage > 50 V – Safety specifications
- IEC 62471/ GB/T20145 Photo biological safety of lamps.
- EN 55015 Limits and methods of measurement of radio disturbance characteristics of electrical lighting and similar equipment
- EN 61000-3-2 Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)
- EN 61000-3-3 Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems, for equipment with rated current ≤ 16 A per phase and not subject to conditional connection
- EN 61547 Equipment for general lighting purposes - EMC immunity requirements

Disposal information

- Lamps with WEEE sign can be returned at specific collection points.
- LED lamps have to be disposed as special waste

